

## Hera-F85

### 18W Fixed LED Recessed Downlight




Luminaire Finishes

White (WH)  Black (BK)

Interchangeable Baffle Finishes

White (WH)  Black (BK)  Specular (SP)

Gold (GD)



#### Accessories

**HERA-F85-HC**  
Honeycomb louvre



**HERA-F85-ELIP**  
Elliptical lens



The Hera-F85 is a fixed, deep set LED luminaire providing low-glare light distribution in different beam options and baffle finishes. Made of high quality materials including a die cast aluminium housing and a high purity optical lens, Hera has been designed to be easy to maintain, adaptable and efficient.

Purpose built for a range of residential, commercial and hospitality applications, Hera-F85 integrates Zhaga compliant Bridgelux LED technology and a mains dimmable driver as standard with optional DALI-2 or Bluetooth dimming. Hera offers a 5 year warranty.

- Luminaire wattage: 18W (System 20W)
- Luminous flux: 1570-1742Lm<sup>2</sup>
- Luminaire efficacy: 81.80Lm/W<sup>1</sup>
- Correlated colour temperature: 2700K, 3000K, 4000K
- Colour rendering index: >90<sup>3</sup>
- Mac-Adams Ellipse: 3-SDCM
- LED brand: Bridgelux COB LED
- Glare control: UGR<19
- Symmetrical distribution: 15°, 24°, 36°
- Outer trim Ø94mm; Ceiling cut-out Ø85mm
- Ingress protection rating: IP44 standard (From underside)
- Luminaire finishes: White, Black
- Baffle Options: White, Black, Specular, Gold
- Longevity: >50,000Hrs L80 L10
- Driver: Mains-dimmable LED driver as standard
- Dimming: DALI-2/DSI, BLE (basicDIM Wireless / Casambi) on request<sup>4</sup>
- Weight: 410g (excluding driver)
- Warranty: 5 years<sup>5</sup>

Model	LED Output <sup>2</sup>	Luminous Flux <sup>2</sup>	LED Wattage	System Wattage	CCT	CRI <sup>3</sup>	Distribution
HERA-F85-18W-27K	1882Lm	1570Lm	18W	20W	2700K	>90	15°, 24°, 36°
HERA-F85-18W-3K	1960Lm	1636Lm	18W	20W	3000K	>90	15°, 24°, 36°
HERA-F85-18W-4K	2087Lm	1742Lm	18W	20W	4000K	>90	15°, 24°, 36°


For Mains-dimming add suffix MD  
For DALI-2 dimming add suffix D  
For BLUETOOTH dimming add suffix BT

Example product order code configuration: HERA-F85-18W-3K-36-D-(WH/WH)


Model	Wattage	CCT	Distribution	Driver	Luminaire Finish / Baffle Finish
HERA-F85	18W	3K	36	D	WH/WH

#### Light Distribution

HERA-F85-18W-3K-36



#### Cone Diagram



1 Luminaire efficacy based on CCT 3000K; CCT variations will alter efficacy  
2 +/- 10% stated initial LED and luminous flux tolerance  
3 Colour Rendering Index: >90 Standard (Bridgelux COB Series)  
4 Additional charges apply for non-standard colour/s, accessories and dimming options  
5 Five year manufacturer's warranty covering product defects and performance deficiencies